

ZX16-SQ-SOI

LED Area Accent . ZX16 Series



IP67

Materials: Machined aluminum(6061-T6)
Stainless steel(SS304)hardware.

Fitting: 1/2"-14 NPS male thread.

Input Voltage: 12V AC/DC

Wattage: 9W max.

Light Source: MR16 SORAA® LED lamp
(GU5.3 socket).

Dimming: MLV / ELV.


Installation and Adjustment



TURN OFF POWER BEFORE AND DURING WIRING TO POWER SUPPLY

Installation/Service must be done by a qualified electrician, and compliant with NEC and Local Codes.

1. Secure the fixture fitting to the 1/2"-14 NPS female thread on mounting device (plate, box, spike, etc.).
2. Connect 18AWG solid input wires to the 12V power source using appropriate wire connectors.
3. Secure the mounting device with the fixture to mounting surface. For HK original mounting accessory, see the individual instruction for further detail of the installation.
4. To adjust tilting position of fixture, loosen tilt adjustment screw with 9/64" hex key, aim the fixture body and tighten the screw to secure the fixture in place. Do not tighten more than necessary.
5. To adjust rotating position of the fixture, loosen rotation adjustment screw with 5/64" hex key, aim the fixture stem and tighten the screw to secure the fixture in place. Do not tighten more than necessary.




Lamp Replacement




TURN OFF POWER AND KEEP FIXTURE COOL DURING MAINTENANCE SERVICE

1. Use the 9/64" hex key to loosen the hood locking screw(8-32UNC hex cap screw) on the top of the hood and remove the hood from fixture body, and access the LED module and reflector assembly.
2. Remove the existing SORAA MR16 lamp by pulling it out from the housing, and install the new SORAA MR16 lamp in the fixture body, ensuring the base of the lamp lines up with the GU5.3 socket.
3. Press down firmly on the lamp to ensure the SORAA Thermobuster pins are in full contact with the lamp.
4. Replace the fixture hood onto the fixture body(Do not tighten more than necessary). Make sure the O-ring is in the proper groove on the fixture body, to form a watertight seal.




For Glare Shield Adjustment & Optical Accessory Setting

Glare Shield Setting



1. Use the 5/64" hex key to loosen the screw(8-32UNC set screw) on the bottom of the glare shield. Move the glare shield to the desired position, and tighten the screw (⚠ do not overtighten).

For Optical Accessory Setting



1. Use the 9/64" hex key to loosen the hood locking screw(8-32UNC hex cap screw) on the top of the hood and remove the hood from fixture body.
2. The hood accepts up to 3 accessories(hexcel louver, optical lenses, dichroic color filters, etc.). Secured in place with metal snap ring.
3. Pull out the snap ring from the hood.
4. Install or replace the accessory by placing it into the hood.
5. Replace the snap ring into the hood and push it into the groove(inside of the hood).
6. Replace the fixture hood onto the fixture body(Do not tighten more than necessary). Make sure the O-ring is in the proper groove on the fixture body, to form a watertight seal.