

ZXL-SL-FM

LED Step Marker . ZXL-SL Series



Materials: Machined aluminum(6061-T6)
Stainless steel(SS304)hardware.

Fitting: 2 x 1/2" Conduit fitting

Input Voltage: 12V AC/DC

Wattage: 6W max.

Light Source: HK LED module.

Dimming: MLV / ELV.

Installation and Adjustment



TURN OFF POWER BEFORE AND DURING WIRING TO POWER SUPPLY

Installation/Service must be done by a qualified electrician, and compliant with NEC and Local Codes.

1. Loosen 2 x mounting screws and pull LED module out with 7/64 hex drive key.
2. Loosen the 4x screws on the mounting bracket, attach the bracket to the supporting structure (e.g., 2x4 lumber), and adjust the position of the back box so that the front of back box is flush with the surface of the wall. Tighten 4 X adjusting screws once in position,
3. Bring the power lines into the back box through one or two of 1/2" conduit fitting on both sides of the box.
4. Connect the wires from LED module to the 12V power line.
5. Set the LED module back and tighten 2 x mounting screws

